

# HASLER

## WJ65, WJ95, WJ110 – January 2012 USPS Rate Change - Loading Rates

To install the January 2012 USPS Rate Change on the WJ65, WJ95, WJ110:


1. Press the **LOCK** button.



2. Press the button below **SUPERVIS**.



3. Enter the Supervisor PIN Code, **9430**.



4. Using the down arrow button, select **Option 4, LOAD FROM MEMORY CARD**.

- Press **OK**.



© 2012 Neopost USA Inc. All rights reserved.


No part of this document may be reproduced or distributed in any form or by any means without the express written permission of an authorized representative of Neopost USA. This document and all information contained herein are confidential and may only be disclosed as necessary to support customer use of the equipment.

### Limitations of this Document

The information presented herein is subject to change. Neopost USA Inc. ASSUMES NO LIABILITY WHATSOEVER FOR ANY LOSSES OR DAMAGES RESULTING FROM USE OF THIS INFORMATION.

# HASLER

5. Insert the memory card with the model numbers facing up into the slot on the side of the machine.  
- Press **OK**.




6. **LOAD FROM MEMORY CARD** and the rate to be loaded will be displayed on the screen.  
- The rate on the screen should read **US1201R**.  
- Press **OK**.




7. The mailing machine will prompt to replace the previous rate file.  
- Ensure that the oldest rate file, **US1101R** is selected.  
- Press **OK**.



8. Wait for the new rates to load.



9. When the new rates have been loaded, the mailing machine will display **LOAD FROM MEMORY CARD LOADING COMPLETE**.



# HASLER

**10.** The new rates have been successfully loaded.

- Remove the Rate Card from the mailing machine.
- Press the **LOCK** button to return to the main screen.



**11.** The new rates will not become active until the USPS effective date of January 22, 2012.

**The Default Postage Value may need to be changed after the rates are active.  
This change should be made on January 22, 2012.**